

The ANY-maze Radio remote control



Overview

The ANY-maze Radio remote control provides a simple and practical way to remotely start tests. It consists of two parts: a receiver, which connects to a USB port; and the remote control itself, which has two buttons and works through walls and at distances of up to 50 metres.

Receiver

- Can be paired with up to 16 remote controls.

- Paired remote controls can be given friendly names, such as "Plusmaze remote".
- Connects directly to a USB port.

Remote control

- Two independent buttons allow you to start tests in two different apparatus.
- Works at up to 50m line-of-sight.
- Works at 10m or more through a wall (through-wall range depends on wall construction).
- Battery lasts for at least 6 months in normal use.

Technical specification

Receiver	
Connection type	USB (USB1.1, USB2.0, USB3.0 compatible)
Power	Powered from USB
Maximum current drawn from USB	100mA
Radio frequency	2.4 GHz
Approvals / Compliance	IC and FCC approved / CE and ETSI compliant
Remote control	
Number of buttons	2
Power	CR2032 battery
Range	≥50m (line of sight), ≥10m (through wall, typical)
Approvals / Compliance	IC and FCC approved / CE and ETSI compliant