

# The ANY-maze Speaker



## Overview

The ANY-maze speaker is ideal for playing tones, white-noise or sound files during a test. The speaker is contained in a small case with a threaded mounting ring for simple installation into surfaces up to 1/2" thick

Note that the speaker requires a sound generating device, such as the ANY-maze Audio interface.

## Details

- Designed to work with the ANY-maze Audio interface, but can also be used with other sound generating devices.
- Can generate loud sounds. A 2.5KHz tone played by the ANY-maze Audio interface at 100% volume, has a sound pressure level of 108dBA measured 50cm from the front of the speaker.

## Technical specification

<b>Speaker</b>	
Rated power	10 W
Maximum power	20 W
Nominal impedance	4 Ohm
Frequency response	460 – 20,000 Hz
<b>Mechanical</b>	
Overall diameter	54.1mm (2.13")
Depth	24.0mm (0.94")
Mounting hole diameter	44.0mm (1.73")
Maximum panel thickness	12.7mm (0.50")
Cable length	100cm (3' 3")