

# The ANY-maze Operant interface C



## Overview

The ANY-maze Operant interface C is designed to directly connect ANY-maze to the popular range of Operant conditioning equipment manufactured by Coulbourn instruments.

## General

- Allows ANY-maze to read inputs and control outputs.
- Works as a drop-in replacement for existing Coulbourn Instruments Environment Connection Boards (ECBs).
- Connects directly to the computer via USB; no Coulbourn Habitest Linc interface is required.
- The interface can either be powered from the ANY-maze Operant hub, or from a standalone power supply.

## Inputs

- 4 *Switch* Inputs, which use the same RJ12 connectors as the Coulbourn ECB and are labelled in the same way.
- 1 *Audio* input which replicates an input on the rear of the Habitest Linc interface.

## Outputs

- 2 *Cue* outputs, 2 *Feeder* outputs, 4 *Spare* outputs, 1 *Tone* output and 1 *House light* output. These outputs use the same RJ12 connectors as the Coulbourn ECB and are labelled in the same way.
- 2 Analogue (*Prog*) outputs and 2 *Auxiliary* outputs, these replicate outputs on the rear of the Habitest Linc interface.
- All outputs (except *Prog*) can optionally dim lights or LEDs connected to them.

## Technical specification

<b>Connection to PC</b>									
Connection type	USB (USB1.1, USB2.0, USB3.0 compatible)								
Interface power	The interface itself is powered from the USB bus								
Maximum current drawn from USB	130mA								
<b>Recommended power supply</b>									
Input voltage	90 - 264 VAC								
Output voltage	28 VDC								
Output current	2.5A minimum								
<b>LED indicator</b>									
LED (note 1)	<table> <tbody> <tr> <td>Off</td> <td>No power connected</td> </tr> <tr> <td>Red</td> <td>Connected to 28V power but not to USB</td> </tr> <tr> <td>Flashing green</td> <td>Connected to USB but not to 28V</td> </tr> <tr> <td>Solid green</td> <td>Connected to USB and 28V</td> </tr> </tbody> </table>	Off	No power connected	Red	Connected to 28V power but not to USB	Flashing green	Connected to USB but not to 28V	Solid green	Connected to USB and 28V
Off	No power connected								
Red	Connected to 28V power but not to USB								
Flashing green	Connected to USB but not to 28V								
Solid green	Connected to USB and 28V								
<b>Standard Inputs</b>									
Number of channels	4 in total - 1 on each <i>Switch</i> input								
Input isolation	3750 V <sub>RMS</sub>								
Input voltage range	-28V – 0V								
Connector	Same RJ12 connectors as Coulbourn ECB								
<b>Audio input</b>									
Number of channels	1								
Connector	3.5mm jack, connects directly to <i>Speaker</i> phono output, same as Coulbourn ECB								
<b>Standard outputs</b>									
Number of channels	16 in total: 3 on each of 2 <i>Cue</i> outputs 2 on each of 2 <i>Feeder</i> outputs 1 on each of 4 <i>Spare</i> outputs 1 on <i>Tone</i> output 1 on <i>House light</i> output								
Output isolation	3750 V <sub>RMS</sub>								
Output on voltage (note 2)	-28V								
Output off voltage (note 3)	GND								
Maximum current per output	1.5A								
Light/LED dimming capability	Available on all channels (note 4)								
Connectors	Same RJ12 connectors as Coulbourn ECB								
<b>Auxiliary outputs</b>									
Number of channels	2								
Output isolation	3750 V <sub>RMS</sub>								
Output on voltage (note 2)	-28V								
Output off voltage (note 3)	GND								
Maximum current per output	1.5A								
Connectors	4-way pluggable screw terminal block								
<b>Analogue (Prog) outputs</b>									
Number of channels	2								
Output range	0 – 2.5VDC								
Connectors	2 x 2.5mm jack connectors								

**Notes**

1. LED can be suppressed, which is useful for tests performed in darkness and/or to avoid providing potential cues to the animals.
2. When on, each output signal pin can sink a maximum of 0.5A. The absolute maximum current across all outputs is 2.5A.
3. When off, each output signal pin can source almost no current (it is pulled high through a 10K resistor).
4. Light dimming is performed using Pulse Width Modulation (PWM) at 320Hz.

**Supported Coulbourn Instruments components**

If you have a component that is not listed here please contact us at [support@anymaze.com](mailto:support@anymaze.com) to confirm compatibility.

**Audio stimuli**

- H12-02M-2.9 2.9 KHz high-power tone module - Mouse
- H12-02M-4.5 4.5 KHz high-power tone module – Mouse
- H12-02R-2.9 2.9 KHz high-power tone module – Rat
- H12-02R-4.5 4.5 KHz high-power tone module – Rat
- H12-04M Mouse buzzer
- H12-05R Clicker module - Rat
- H12-07 Seven-tone audio cue
- H12-07MOD-Leuven Seven-tone audio cue
- H12-08 White noise generator
- H12-09 Seven-level audio attenuator
- A12-33 (x10) Programmable audio signal generator (range set to x10)
- A12-33 (x100) Programmable audio signal generator (range set to x100)
- A69-20 Tone/white noise generator

**Doors**

- H10-37 Runway guillotine door lifter
- H24-01M-CA Access controlled lickometer - Mouse
- H24-01R-CA Access controlled lickometer - Rat

**Dry feeders**

- H14-01M Pellet delivery trough - Mouse
- H14-01R Pellet delivery trough - Rat
- H14-22M-20 Pellet feeder - Mouse 20mg
- H14-23M Pellet feeder 20mg - Mouse
- H14-22M-20SP Pellet feeder 20mg - Mouse on Rat panel
- H14-23M-SP01 Pellet feeder 20mg - Mouse on Rat panel
- H14-22R-45 Pellet feeder 45mg - Rat
- H14-23R Pellet feeder 45mg - Rat
- H14-23R-97 Pellet feeder 97mg - Rat
- H14-06R Combination dipper/pellet trough
- H14-10R Grain feeder

- H14-02M Auto feeder - Mouse
- H14-02R Auto feeder - Rat

### Fans

- H29-05M Fan module - Mouse
- H29-05R Fan module - Rat

### Hand switches

- H21-01 Hand (shaping) switch
- H21-02M Experimenter's manual switch module - Mouse
- H21-02R Experimenter's manual switch module - Rat

### House lights

- H11-01M House light – Mouse
- H11-01R House light – Rat
- H11-01M-LED LED House light – Mouse
- H11-01R-LED LED House light – Rat

### Levers

- H21-03M Response lever - Mouse
- H21-03M-SP01 Response lever - Mouse on Rat panel
- H21-03R Response lever - Rat
- H21-05M Omnidirectional response lever - Mouse
- H21-05R Omnidirectional response lever - Rat
- H23-17M Retractable lever - Mouse
- H23-17MA Retractable lever - Mouse
- H23-17R Retractable lever - Rat
- H23-17RA Retractable lever - Rat
- H23-17R-TIL Transilluminated retractable lever - Rat

### Liquid feeders

- H14-04M Liquid solenoid valve - Mouse
- H14-04R Liquid solenoid valve - Rat
- H14-05M Liquid dipper - Mouse
- H14-05M/R Liquid dipper - Mouse on Rat panel
- H14-05R Liquid dipper - Rat

### Nose poke holes

- H21-09M Nose poke - Mouse
- H21-09R Nose poke - Rat
- H21-09M-W Nose poke all white LEDs - Mouse
- H21-09R-W Nose poke all white LEDs - Rat

- H21-10M Nose poke with light diffuser - Mouse
- H21-10R Nose poke with light diffuser - Rat
- H21-09M-MOD Nose poke with all white LEDs and olfactory inlet - Mouse
- H21-09R-MOD Nose poke with all white LEDs and olfactory inlet - Rat
- H21-09M-CA Nose poke with access control - Mouse
- H21-09R-CA Nose poke with access control - Rat

### Olfactory stimuli

- H15-03 Olfactory stimulus control

### Other response devices

- H22-01 Response wheel
- H25-01 Ceiling chain
- H25-06 Universal ceiling mount bump rod

### Pecking keys

- H21-15R Bird pecking key
- H21-17R Bird pecking key with 3-color cue
- H21-19R Bird pecking key with 7-pattern display

### Photobeams

- H20-93 Single photocell sensor
- H20-93A Single photocell sensor
- H20-94 Single photocell sensor
- H20-95 Photocell sensor bar
- H20-95-X Photocell sensor bar

### Running wheels

- H10-38R Shockable running wheel
- H10-38R-CMT Cage mount shockable running wheel

### Shockers

- H13-01 2-Pole shocker
- H13-15 Precision-regulated shocker
- H13-16 Precision-regulated programmable shocker
- H13-16 REV A Precision-regulated programmable shocker
- H13-17 Precision-regulated programmable shocker
- H13-17A Precision-regulated programmable shocker

### Stimulus lights

- H11-03M Single high-bright cue – Mouse
- H11-03M-RL Single high-bright cue, red lens – Mouse
- H11-03M-LED Single high-bright cue LED – Mouse

- H11-03M-LED-RL Single high-bright cue LED red – Mouse
- H11-03R Single high-bright cue – Rat
- H11-03R-RL Single high-bright cue, red lens – Rat
- H11-03R-LED Single High-Bright Cue LED – Rat
- H11-03R-LED-RL Single high-bright cue LED red – Rat
- H11-05 Bright ceiling-mount light
- H11-05-LED Bright ceiling-mount light LED
- H11-02M Triple cue lamp – Mouse
- H11-02R Triple cue lamp – Rat
- H11-02R-LED LED Triple cue lamp – Rat
- H11-07M Seven-pattern display, red – Mouse
- H11-07M-G Seven-pattern display, green – Mouse
- H11-07M-Y Seven-pattern display, yellow – Mouse
- H11-07R Seven-pattern display, red – Rat
- H11-07R-G Seven-pattern display, green – Rat
- H11-07R-Y Seven-pattern display, yellow – Rat
- H91-16-INT-CTRL In-line light intensity control
- A21-10 Light intensity (and colour) controller

### Syringe pumps

- E73-02 Selectable speed infusion pump

### Miscellaneous components

- H24-05 Contact sensor
- H24-61 Infrared activity monitor (ceiling-mount)
- A24-72 Resistive bridge transducer monitor